

# ORIGINAL MINIXEN

Original spare part



## The cost-effective original spare parts

ORIGINAL MINIXEN signal lamps for cars can be used for interior lighting as well as reading lights. Discover these original spare parts from OSRAM with reliable OEM quality and a wide product range.



## Product family datasheet

### Technical data

Product description	Product information		Electrical data				
	Order reference	Application (Category and Product specific)	Power input	Nominal voltage	Nominal wattage	Power input tolerance	Test voltage
ORIGINAL MINIXEN 2886X	2886X	Auxiliary lamp	6 W	12.0 V	6.00 W	±10 %	13.5 V
ORIGINAL MINIXEN 3886X	3886X	Auxiliary lamp	6 W	12.0 V	6.00 W	±10 %	13.5 V

Product description	Photometrical data	Dimensions & weight		Lifespan		Additional product data	Capabilities
	Luminous flux	Length	Diameter	Lifespan B3	Lifespan Tc	Base (standard designation)	Technology
ORIGINAL MINIXEN 2886X	85 lm	26.8 mm	10.0 mm	400 h	1000 h	W2.1x9.5d	AUX
ORIGINAL MINIXEN 3886X	80 lm	27.4 mm	9 mm	400 h	1000 h	BA9s	AUX

Product description	Certificates & standards	Environmental information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)		
	ECE category	Date of Declaration	Primary Article Identifier	Candidate List Substance 1
ORIGINAL MINIXEN 2886X	-	03-07-2024	4050300888668   4008321094667   4052899560604	No declarable substances contained
ORIGINAL MINIXEN 3886X	-	03-07-2024	4050300885896   4008321095787	No declarable substances contained

Product description	Declaration No. in SCIP database
ORIGINAL MINIXEN 2886X	In work
ORIGINAL MINIXEN 3886X	In work

## Product family datasheet

### Application advice

For more detailed application information and graphics please see product datasheet.

### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

